



SLM500L 400 SDM450 CPU 14nm FinFET 64bit ARM 8 A53
 4*1.8GHz Decode/encode 4K@30fps H.265 FHD ISP Android
 10 2GB+16GB 3GB+32GB LTE Cat4 150Mbps
 50Mbps TD-LTE/FDD-LTE/WCDMA/EVDO/TD-SCDMA/CDMA/GSM GNSS 2.4&5G
 WIFI

SLM500L SLM500L-C SLM500L-E* SLM500L-A* SLM500L-LA* SLM500L-
 J* SLM500L-AU* SNM500L.

SLM500L 2.4G/5G WiFi BT GPS 1300W 3D
 POS VR Camera

LTE Cat 4
 150Mbps



FHD 1920x1200 @60pfs

ISP 13M+13M

21MP camera

GNSS

4K @30fps

/
SLM500L-C
LTE FDD: B1/B3/B5/B8
LTE TDD: B34/B38/B39/B40/B41
WCDMA: B1/B8
TD-SCDMA: B34/B39
EVDO/CDMA: BC0
GSM: 900/1800MHz

/ /
SLM500L-E
LTE FDD: B1/B3/B5/B7/B8/B20/B28A
LTE TDD: B38/B40/B41
WCDMA: B1/B5/B8
GSM: 850/900/1800/1900MHz

SLM500L-A*
LTE FDD: B2/B4/B5/B7/B12/B13/B17/B25/B26/B66
WCDMA: B2/B4/B5/B8
GSM: 850/1900MHz

/ /
SLM500L-AU*
LTE FDD: B1/B3/B5/B7/B8/B28
LTE TDD: B40
WCDMA: B1/B5/B8
GSM: 850/900/1800MHz

SLM500L-J*
LTE FDD: B1/B3/B8/B18/B19/B26
LTE TDD: B41
WCDMA: B1/B6/B8/B19

SLM500L-LA*
LTE-FDD: B2/B4/B5/B7/B8/B25/B28/B66
LTE TDD: B40
WCDMA: B2/B5/B8
GSM: 850/900/1900MHz

SNM500L
Wi-Fi & BT

LTE:
Cat 4 FDD: 150Mbps (DL)/50Mbps (UL)
Cat 4 TDD: 117Mbps (DL)/30Mbps (UL)
UMTS:
DC-USDPA: 42Mbps (DL)
HSUPA: 5.76Mbps (UL)
WCDMA: 384Kbps (DL/UL)
TD-SCDMA:
4.2Mbps (DL)/2.2Mbps (UL)
DMA: 512/384/192 0 Td(/)Tj7/